

SVR-1008E



Product Summary

- Embedded Linux
- Mouse, Remote controller, Network
- USB2.0 Memory(FAT 32) Network
- Max. 1080p 5fps
- E-mail, Event Popup, Buzzer, PTZ Preset
- Android, iPhone, iPad

Major Specifications

Model Name		SVR-1008E
System	OS	Embedded Linux
	Control	Mouse, Remote controller, Network
	Hexaplex	Realtime monitoring, Recording, Playback, Backup, Network, Setup
	Upgrade	USB2.0 Memory(FAT 32) Network
Video	Video Input	8 BNC
	Video Output	1 HD-MI, 1 VGA, 1 BNC, 1 RCA (SPOT)
Audio	Audio Input	8 RCA
	Audio Output	HD-MI, RCA
Video Recording	Compression	H.264
	Recording Speed	Max. 30 fps/ch
	Resolution	Max. FHD
	Event	Motion, Sound Detection
Audio Recording	Recording Quality	5 Levels
	Compression	G.711U
Network	Audio Sampling Rate	8KHz
	Network Connection	Ethernet 10/100/1G
	Compression	H.264 / JPEG
	Speed	Max. 1080p 5fps
Backup	Resolution	Max. 1080p
	Backup/Download	USB2.0, Network
Alarm	Format	Video clip(rms, avi), JPEG still image, Log list, Setup data
	Pre/Post-Alarm	5sec / 5sec~5min
	Alarm Action	E-mail, Event Popup, Buzzer, PTZ Preset , Relay, Spot, Remote CMS
Display	Input/Output	4/1 - NC/NO
	HD-MI	FHD, SxGA, XGA
	VGA	FHD, SxGA, XGA
	Spot	SDTV(720x480)
External Interface	Mode	8/4/1/SEQ- LIVE, 8/4/1 -P.B.
	PTZ / Keyboard	2 RS485 - Terminal Block
Storage	ATM / POS	RS232C - Terminal Block / Ethernet POS
	Internal Device / External Device	2 HDD or 1HDD + 1 eSATA
Features	ODD	N/A
	DDNS, DHCP, UPNP	Yes
	VMS, RMS	Windows
	Smartphone (3G/4G)	Android, iPhone, iPad
General	Mac Viewer	Apple Mac OS
	Power Supply	12V/3.3A
	Consumption	40 Watts
	Weight w/o HDD	3Kg
	Dimension	340 x 59 x 300 mm