

SVR-1016E



Product Summary

- Embedded Linux
- Mouse, Remote controller, Network
- USB2.0 Memory(FAT 32) Network
- Max. 1080p 5fps
- E-mail, Event Popup, Buzzer, PTZ Preset
- Android, iPhone, iPad

Major Specifications

Model Name		SVR-1016E
System	OS	Embedded Linux
	Control	Mouse, Remote controller, Network
	Hexaplex	Realtime monitoring, Recording, Playback, Backup, Network, Setup
	Upgrade	USB2.0 Memory(FAT 32) Network
Video	Video Input	16 BNC
	Video Output	1 HD-MI, 1 VGA, 1 BNC
Audio	Audio Input	16 RCA
	Audio Output	HD-MI, RCA
Video Recording	Compression	H.264
	Recording Speed	Max. 30 fps/ch
	Resolution	Max. FHD
	Event	Motion, Sound Detection
Audio Recording	Recording Quality	5 Levels
	Compression	G.711U
Network	Audio Sampling Rate	8KHz
	Network Connection	Ethernet 10/100/1G
	Compression	H.264 / JPEG
	Speed	Max. 1080p 5fps
Backup	Resolution	Max. 1080p
	Backup/Download	USB2.0, Network
	Format	Video clip(rms, avi), JPEG still image, Log list, Setup data
Alarm	Pre/Post-Alarm	5sec / 5sec~5min
	Alarm Action	E-mail, Event Popup, Buzzer, PTZ Preset Relay, Spot, Remote CMS
	Input/Output	4/1 - NC/NO
Display	HD-MI	FHD, SxGA, XGA
	VGA	FHD, SxGA, XGA
	Spot	SDTV(720x480)
	Mode	16/8/4/1/SEQ- LIVE, 16/8/4/1 -P.B.
External Interface	PTZ / Keyboard	2 RS485 - Terminal Block
	ATM / POS	RS232C - Terminal Block / Ethernet POS
Storage	Internal Device / External Device	2 HDD or 1HDD + 1 eSATA
	ODD	N/A
Features	DDNS, DHCP, UPNP	Yes
	VMS, RMS	Windows
	Smartphone (3G/4G)	Android, iPhone, iPad
	Mac Viewer	Apple Mac OS
General	Power Supply	12V/5A
	Consumption	60 Watts
	Weight w/o HDD	3Kg
	Dimension	340 x 59 x 300 mm